



	<b>NT/TE settings port X</b>	
<b>JP1-4</b>	<p>Set all jumpers to the left to select NT mode for port X</p>	<p>Set all jumpers to the right to select TE mode for port X</p>
	<b>Power feeding port X (only for NT mode)</b>	
<b>JP5-8</b>	<p>Power feeding enabled for port X (PFM required)</p>	<p>Power feeding disabled for port X (factory default)</p>

	<b>Status LED</b>
<b>LED</b>	Layer 1 activated Layer 1 deactivated

	<b>Termination of S/T interface port X (100Ω)</b>	
<b>SW1-4</b>	<p>Both switches in ON position activates termination for port X</p>	<p>Both switches in OFF position deactivates termination for port X</p>

	<b>Card ID switches</b>																																				
	Use DIP switches 1 to 3 to set the card ID (very useful for remotely identifying individual cards):																																				
<b>SW5</b>	<table border="1"> <thead> <tr> <th>Card-ID</th> <th>0</th> <th>1</th> <th>2</th> <th>3</th> <th>4</th> <th>5</th> <th>6</th> <th>7</th> </tr> </thead> <tbody> <tr> <td><b>SW5_1</b></td> <td>OFF</td> <td>ON</td> <td>OFF</td> <td>ON</td> <td>OFF</td> <td>ON</td> <td>OFF</td> <td>ON</td> </tr> <tr> <td><b>SW5_2</b></td> <td>OFF</td> <td>OFF</td> <td>ON</td> <td>ON</td> <td>OFF</td> <td>OFF</td> <td>ON</td> <td>ON</td> </tr> <tr> <td><b>SW5_3</b></td> <td>OFF</td> <td>OFF</td> <td>OFF</td> <td>OFF</td> <td>ON</td> <td>ON</td> <td>ON</td> <td>ON</td> </tr> </tbody> </table>	Card-ID	0	1	2	3	4	5	6	7	<b>SW5_1</b>	OFF	ON	OFF	ON	OFF	ON	OFF	ON	<b>SW5_2</b>	OFF	OFF	ON	ON	OFF	OFF	ON	ON	<b>SW5_3</b>	OFF	OFF	OFF	OFF	ON	ON	ON	ON
Card-ID	0	1	2	3	4	5	6	7																													
<b>SW5_1</b>	OFF	ON	OFF	ON	OFF	ON	OFF	ON																													
<b>SW5_2</b>	OFF	OFF	ON	ON	OFF	OFF	ON	ON																													
<b>SW5_3</b>	OFF	OFF	OFF	OFF	ON	ON	ON	ON																													

<b>CON1</b>	<b>PCM out</b>
<b>CON2</b>	<b>PCM in</b>
<b>CON3</b>	<b>Onboard PFM connector (available optionally)</b>
<b>CON4</b>	<b>Power connector</b> Connector for the external power feeding module to feed S/T interfaces of up to 4 duo- or quadBRI cards (available optionally)