



JP1-2	NT/TE settings port X	
	Set all jumpers to the right to select NT mode for port X	Set all jumpers to the left to select TE mode for port X
JP3-4	Pinout	
	E1 Pinout (1,2,4,5)	S2M Pinout(3,4,5,6)
JP5	Power supply configuration	
	Uses 3.3V from the PCI bus (only available in 3.3V PCI slots)	Generates 3.3V out of the 5V from the PCI bus (factory default)

LED1-2	Status LED's for port X	
	1 ● 3, 2 = Framing 2 ● 4, 3, 4 = CRC4 Multiframing ● established ● not established	

SW1-2	Termination of interface port X	
	Right switch: ON Termination 75 Ω	Right switch: OFF Termination 120 Ω

SW3-4	Card ID switches																																				
	Use DIP switches 1 to 3 to set the card ID (very useful for remotely identifying individual cards):																																				
	<table border="1"> <thead> <tr> <th>Card-ID</th> <th>0</th> <th>1</th> <th>2</th> <th>3</th> <th>4</th> <th>5</th> <th>6</th> <th>7</th> </tr> </thead> <tbody> <tr> <td>SW3_1</td> <td>OFF</td> <td>ON</td> <td>OFF</td> <td>ON</td> <td>OFF</td> <td>ON</td> <td>OFF</td> <td>ON</td> </tr> <tr> <td>SW3_2</td> <td>OFF</td> <td>OFF</td> <td>ON</td> <td>ON</td> <td>OFF</td> <td>OFF</td> <td>ON</td> <td>ON</td> </tr> <tr> <td>SW3_3</td> <td>OFF</td> <td>OFF</td> <td>OFF</td> <td>OFF</td> <td>ON</td> <td>ON</td> <td>ON</td> <td>ON</td> </tr> </tbody> </table>	Card-ID	0	1	2	3	4	5	6	7	SW3_1	OFF	ON	OFF	ON	OFF	ON	OFF	ON	SW3_2	OFF	OFF	ON	ON	OFF	OFF	ON	ON	SW3_3	OFF	OFF	OFF	OFF	ON	ON	ON	ON
Card-ID	0	1	2	3	4	5	6	7																													
SW3_1	OFF	ON	OFF	ON	OFF	ON	OFF	ON																													
SW3_2	OFF	OFF	ON	ON	OFF	OFF	ON	ON																													
SW3_3	OFF	OFF	OFF	OFF	ON	ON	ON	ON																													

CON1	PCM out
CON2	PCM in