



	<b>NT/TE settings port X</b>	
<b>JP1-2</b>	<p>Set all jumpers to the left to select NT mode for port X</p>	<p>Set all jumpers to the right to select TE mode for port X</p>

	<b>Status LED</b>
<b>LED</b>	Layer 1 activated Layer 1 deactivated

	<b>Termination of S/T interface port X (100Ω)</b>	
<b>SW1-2</b>	<p>Both switches in ON position activates termination for port X</p>	<p>Both switches in OFF position deactivates termination for port X</p>

	<b>Card ID switches</b>				
<b>SW3</b>	Use DIP switches 1 to 2 to set the card ID (very useful for remotely identifying individual cards):				
	<b>Card-ID</b>	<b>0</b>	<b>1</b>	<b>2</b>	<b>3</b>
	<b>SW3_1</b>	OFF	ON	OFF	ON
	<b>SW3_2</b>	OFF	OFF	ON	ON

<b>CON1</b>	<b>miniPCI connector</b> Conenctor for the miniPCI card
<b>CON2</b>	<b>Connector for the RJ45 board</b>
<b>CON3</b>	<b>PCM Connector</b>