







<b>JP1-4</b>	<b>NT/TE settings port X</b>	
	 Set all jumpers to the left to select NT mode for port X	 Set all jumpers to the right to select TE mode for port X

<b>LED</b>	<b>Status LED</b>
	 Layer 1 activated  Layer 1 deactivated

<b>SW1-4</b>	<b>Termination of S/T interface port X (100Ω)</b>	
	 Both switches in ON position activates termination for port X	 Both switches in OFF position deactivates termination for port X

<b>SW5</b>	<b>Card ID switches</b>			
	Use DIP switches 1 to 2 to set the card ID (very useful for remotely identifying individual cards):			
	Card-ID	0	1	2
SW2_1	OFF	ON	OFF	ON
SW2_2	OFF	OFF	ON	ON

<b>CON1</b>	<b>miniPCI connector</b> Conenctor for the miniPCI card
<b>CON2</b>	<b>Connector for the RJ45 board</b>
<b>CON3</b>	<b>Connector for the RJ45 board</b>