



JP1	NT/TE settings port X	
	Set all jumpers to the right to select NT mode for port X	Set all jumpers to the left to select TE mode for port X
JP2	Pinout	
	E1 Pinout (1,2,4,5)	S2M Pinout(3,4,5,6)
JP3	Power supply configuration	
	Uses 3.3V from the PCI bus (only available in 3.3V PCI slots)	Generates 3.3V out of the 5V from the PCI bus (factory default)

LED1-2	Status LED's for port X	
	1 ● 2 = Framing 2 ● 3, 4 = CRC4 Multiframeing ● established ● not established	

SW1	Termination of interface port X																																					
	Right switch: ON Termination 75 Ω	Right switch: OFF Termination 120 Ω																																				
SW2	Card ID switches																																					
	Use DIP switches 1 to 3 to set the card ID (very useful for remotely identifying individual cards):																																					
	<table border="1"> <thead> <tr> <th>Card-ID</th> <th>0</th> <th>1</th> <th>2</th> <th>3</th> <th>4</th> <th>5</th> <th>6</th> <th>7</th> </tr> </thead> <tbody> <tr> <td>SW2_1</td> <td>OFF</td> <td>ON</td> <td>OFF</td> <td>ON</td> <td>OFF</td> <td>ON</td> <td>OFF</td> <td>ON</td> </tr> <tr> <td>SW2_2</td> <td>OFF</td> <td>OFF</td> <td>ON</td> <td>ON</td> <td>OFF</td> <td>OFF</td> <td>ON</td> <td>ON</td> </tr> <tr> <td>SW2_3</td> <td>OFF</td> <td>OFF</td> <td>OFF</td> <td>OFF</td> <td>ON</td> <td>ON</td> <td>ON</td> <td>ON</td> </tr> </tbody> </table>	Card-ID	0	1	2	3	4	5	6	7	SW2_1	OFF	ON	OFF	ON	OFF	ON	OFF	ON	SW2_2	OFF	OFF	ON	ON	OFF	OFF	ON	ON	SW2_3	OFF	OFF	OFF	OFF	ON	ON	ON	ON	
Card-ID	0	1	2	3	4	5	6	7																														
SW2_1	OFF	ON	OFF	ON	OFF	ON	OFF	ON																														
SW2_2	OFF	OFF	ON	ON	OFF	OFF	ON	ON																														
SW2_3	OFF	OFF	OFF	OFF	ON	ON	ON	ON																														

CON1	PCM out
CON2	PCM in