



	<b>NT/TE settings port X</b>	
<b>JP1</b>	Set all jumpers to the right to select NT mode for port X	Set all jumpers to the left to select TE mode for port X
	<b>Pinout</b>	
<b>JP2</b>	E1 Pinout (1,2,4,5)	S2M Pinout(3,4,5,6)
	<b>Power supply configuration</b>	
<b>JP3</b>	Uses 3.3V from the PCI bus (only available in 3.3V PCI slots)	Generates 3.3V out of the 5V from the PCI bus (factory default)

	<b>Status LED's for port X</b>
<b>LED1-2</b>	1 ● 2 = Framing 2 ● 3, 4 = CRC4 Multiframeing ● established ● not established

	<b>Termination of interface port X</b>																																				
<b>SW1</b>	Right switch: ON Termination 75 Ω	Right switch: OFF Termination 120 Ω																																			
	<b>Card ID switches</b>																																				
<b>SW2</b>	Use DIP switches 1 to 3 to set the card ID (very useful for remotely identifying individual cards):																																				
	<table border="1"> <thead> <tr> <th>Card-ID</th> <th>0</th> <th>1</th> <th>2</th> <th>3</th> <th>4</th> <th>5</th> <th>6</th> <th>7</th> </tr> </thead> <tbody> <tr> <td>SW2_1</td> <td>OFF</td> <td>ON</td> <td>OFF</td> <td>ON</td> <td>OFF</td> <td>ON</td> <td>OFF</td> <td>ON</td> </tr> <tr> <td>SW2_2</td> <td>OFF</td> <td>OFF</td> <td>ON</td> <td>ON</td> <td>OFF</td> <td>OFF</td> <td>ON</td> <td>ON</td> </tr> <tr> <td>SW2_3</td> <td>OFF</td> <td>OFF</td> <td>OFF</td> <td>OFF</td> <td>ON</td> <td>ON</td> <td>ON</td> <td>ON</td> </tr> </tbody> </table>	Card-ID	0	1	2	3	4	5	6	7	SW2_1	OFF	ON	OFF	ON	OFF	ON	OFF	ON	SW2_2	OFF	OFF	ON	ON	OFF	OFF	ON	ON	SW2_3	OFF	OFF	OFF	OFF	ON	ON	ON	ON
Card-ID	0	1	2	3	4	5	6	7																													
SW2_1	OFF	ON	OFF	ON	OFF	ON	OFF	ON																													
SW2_2	OFF	OFF	ON	ON	OFF	OFF	ON	ON																													
SW2_3	OFF	OFF	OFF	OFF	ON	ON	ON	ON																													

<b>CON1</b>	PCM out
<b>CON2</b>	PCM in