



	<b>NT/TE settings port X</b>	
<b>JP1</b>	Set all jumpers to the left to select NT mode for port X	Set all jumpers to the right to select TE mode for port X

	<b>Status LED</b>
<b>LED</b>	● Layer 1 activated ● Layer 1 deactivated

	<b>Termination of S/T interface port X (100Ω)</b>	
<b>SW1</b>	Both switches in ON position activates termination for port X	Both switches in OFF position deactivates termination for port X

	<b>Card ID switches</b>	
<b>SW2</b>	Use DIP switches 1 to 2 to set the card ID (very useful for remotely identifying individual cards):	
	Card-ID	0 1 2 3
	SW2_1	OFF ON OFF ON
	SW2_2	OFF OFF ON ON

<b>CON1</b>	<b>miniPCI connector</b> Conenctor for the miniPCI card
<b>CON2</b>	<b>Connector for the RJ45 board</b>
<b>CON3</b>	<b>PCM Connector</b>